

Radiotron

UX-864

A General Purpose, Non-microphonic Tube

Possessing superior rigidity of construction, UX-864 may be used to advantage by amateurs in the design of their receivers and their microphone amplifiers.

Its freedom from microphonic noises, even when subjected to continuous vibration; its economy of operation, its small over-all dimensions—all these are features which will establish UX-864 as an important contribution to the improvement of amateur reception and transmission.

Sensitive in performance, yet free from microphonic disturbances,



Filament volts	.	.	.	1.1
Filament amperes	.	.	.	0.25
Plate volts	.	.	.	90
Grid bias volts	.	.	.	-4.5
Plate current (m.a.)	.	.	.	2.5
Plate resistance (ohms)	.	.	.	15,500
Amplification factor	.	.	.	6.6
Maximum length	.	.	.	4"
Maximum diameter	.	.	.	1 3/16"

Radiotron UX-864 will be appreciated by those amateurs who desire improved tube performance.

RCA VICTOR COMPANY, INC.

New York—261 Fifth Avenue

Atlanta—101 Marietta Street

Chicago—100 West Monroe Street

Dallas—Santa Fe Building

San Francisco—235 Montgomery Street